



Digital Heaven

DH_RetroTV for Final Cut

Introduction:

DH_RetroTV is a transition effect for Final Cut Pro/Express that recreates an old TV switching on, changing channel or switching off.

To complete the retro experience, DH_RetroTV comes with five specially created and royalty-free sound effects.

If you find this plug-in useful then please do tell your friends and colleagues but please don't just give them a copy.... We deliberately make all our plug-ins available individually so they are as affordable as possible.

The more plug-ins we sell, the more we will be encouraged to develop new and useful plug-ins in the future.

Installation:

Final Cut Pro v4 (or later) on OSX

To install for all users (requires administrator privileges), copy the DH_RetroTV plug-in to:
Macintosh HD/Library/Application Support/Final Cut Pro System Support/Plugins

To install for current user only, copy the DH_RetroTV plug-in to:
Macintosh HD/Users/[Currentusername]/Library/Preferences/Final Cut Pro User Data/Plugins

Final Cut Express v2 (or later) on OSX

To install for all users (requires administrator privileges), copy the DH_RetroTV plug-in to:
Macintosh HD/Library/Application Support/Final Cut Express System Support/Plugins

To install for current user only, copy the DH_RetroTV plug-in to:
Macintosh HD/Users/[Currentusername]/Library/Preferences/Final Cut Express User Data/Plugins

In both Final Cut Pro and Express, DH_RetroTV will appear in the Video Transitions > Digital Heaven folder of the Effects Browser and in the Effects > Video Transitions > Digital Heaven menu.

Controls:

Effect Type (popup menu)

Switch On

This replicates an old TV switching on and is designed to be used at the front of a clip so the incoming image appears from black.

Channel Change

This replicates changing the channel on an old TV and is designed to be used between two clips.

Switch Off

This replicates an old TV switching off and is designed to be used at the end of a clip so the outgoing image disappears to black.

Switch On

Picture Roll

Enables or disables picture rolling when the Effect Type is set to Switch On.

Channel Change

Wigginess (0-10, default=10)

Sets the amount of wiggle in the image when the Effect Type is set to Channel Change.

Noiseiness (0-10, default=10)

Sets the amount of noise in the image when the Effect Type is set to Channel Change.

Sound Effects:

Five specially created and royalty-free sound effects are included with DH_RetroTV. The effects are stereo 48Khz, 16 bit AIFF files.

Switch_01.aif

Switch_01.aif

Noise_01.aif

Noise_02.aif

Noise_03.aif

Simply import to your project and place at the desired point in the sequence.

Need help with DH_RetroTV? Email us at support@digital-heaven.co.uk

©2006 Digital Heaven Limited, London UK www.digital-heaven.co.uk